

# WKS-IR Receiver



Remotely controls a single 110v motor from up to 60 feet away. Processor face plate doubles as a manual override switch. The 110v receiver has a 3 minute maintained contact

Voltage	110-120v AC
Frequency	60Hz
Amperage	4A
Capacity	480v A
Operating ambient temp.	-5 C to +50 C
Output duration	3 minutes
Housing Size	2-3/4" W x 2-3/4" H
Face plate available in white or almond	

WKS-IR AC Receiver

